

TAJFUN 1000 50/70 MHz



PA TAJFUN 1000 50/70MHz

Cena

Predajná cena bez DPH: 2142,00 €

[Opýtajte sa na tento produkt](#)

Výrobca: [VH Electronics](#)

Popis produktu

**New robust Heatsink + Auxiliary small turbine.
USB & LAN as standard.**



TAJFUN 1000 is small, lightweight but robust LDMOS Power Amplifier

- Frequency Coverage: 50 and 70 MHz
- Operating Mode: FM, CW, SSB, DIGI
- Output Power: 1000W CW, 800W SSB, 700W FM a DIGI on 50 MHz
- Push Pull LDMOS
- Input Power: 16-18W default inside 6dB hybrid attenuator (optionally 3dB)
- Power supply inside: 53VDC / 1800W
- Suppression of harmonics: <= 70dBc
- Working temperature: 0-45 °C, Max. humidity 90%
- Protection from: PWR, SWR, Tmax, Imax, Umax/Umin
- Control / Display: color TFT display
- Measurement and display:
 - Current
 - Voltage
 - Power
 - Reflected power
 - Peak power
 - Temperature
- USB - configuration, service
- LAN - remote
- Power supply: 195-277VAC, 45-66Hz
- Dimension: 266x105x294mm
- Coaxial Relay: CX600NC - CX140D (without relay as option)
- Weight: 6,2kg

Instruction manual:

[TAJFUN 1000 50 70MHz](#)

Software:

[Tajfun 1000 servis \(ver.: 1.0.3.3\)](#)

[Tajfun 1000 Remote Display \(ver.: 1.0.0.3\)](#)

[Tajfun 1000 Remote Display \(ver.: 1.0.0.6\)](#)

[Tajfun 1000 Remote Display \(ver.: 1.0.0.8\)](#)